



RUR5

U70/P6 DIP SWITCHES SETTING : 1

Supported bill Ruble (old,new-10, 50, 100, 500, 1000) 5bills.

FUNCTION	SW1	SW2	SW3	SW4	SW5	SW6	SW7	SW8	SW9	SW10
★ 1 Pulse / Ruble 10	OFF	OFF	OFF							
2 Pulse / Ruble 10	OFF	OFF	ON							
3 Pulse / Ruble 10	OFF	ON	OFF							
4 Pulse / Ruble 10	OFF	ON	ON							
5 Pulse / Ruble 10	ON	OFF	OFF							
10 Pulse / Ruble 10	ON	OFF	ON							
20 Pulse / Ruble 10	ON	ON	OFF							
100 Pulse / Ruble 10	ON	ON	ON							
Fast output Pulse <small>Lo= 50ms Hi=100ms</small>				ON						
★ Slow output Pulse <small>Lo= 50ms Hi=300ms</small>				OFF						
Inhibit level Active Low					ON					
★ Inhibit level Active High					OFF					
★ Accept Ruble 10(old,new)						ON				
Reject Ruble 10(old,new)						OFF				
★ Accept Ruble 50(old,new)							ON			
Reject Ruble 50(old,new)							OFF			
★ Accept Ruble 100(old,new)								ON		
Reject Ruble 100(old,new)								OFF		
★ Accept Ruble 500(old,new)									ON	
Reject Ruble 500(old,new)									OFF	
★ Accept Ruble 1000(old,new)										ON
Reject Ruble 1000(old,new)										OFF

★ Manufacture setting

Note: (1)Please reset the bill acceptor after set the dip switch.

(2)Dip switches 1 to 5 are only used for pulse protocol.

DIP SWITCHES SETTING : 2

FUNCTION	SW1	SW2	SW3	SW4	
★ Pulse Normal High	ON				
Pulse Normal Low	OFF				
Pulse Protocol					ON
ICT Protocol					OFF
HOLD			ON		
			OFF		
					ON
					OFF

